

# auxiliaries, remote control and accessories DX<sup>3</sup>



## Technical characteristics p. 68

Pack	Cat.Nos	Auxiliaries	No. of modules
		Mounted on the left-hand side of the devices Possible configuration per device: 3 auxiliaries including 1 control auxiliary Auxiliaries common to MCBs, RCBOs RCDs and isolating switches Allow insertion of the supply busbar	
1	4 062 58	<b>Signalling auxiliaries</b> Auxiliary changeover switch, 6 A - 250 V~ Indicates the position of the contacts of the MCB, RCD or isolating switch	0.5
1	4 062 60	Fault signalling changeover switch, 6 A - 250 V~ Indicates opening on a fault	0.5
1	4 062 62	Auxiliary changeover switch, 6 A - 250 V~ Can be changed to a fault signalling changeover switch	0.5
1	4 062 66	Auxiliary changeover switch + fault signalling changeover switch, 6 A - 250 V~ Can be changed to 2 auxiliary changeover switches	1
		<b>Current shunt trips</b> Used for remote tripping of an MCB, RCD, RCBO or isolating switch at the supply end	
1	4 062 76	12 to 48 V~/=	1
1	4 062 78	110 to 415 V~	1
		<b>Undervoltage releases</b> Time delay adjustable from 0 to 300 ms	
1	4 062 80	24 to 48 V~/=	1
1	4 062 82	230 V~	1
		<b>Stand-alone release for N/C push-button</b> Used for positive safety tripping on the control circuit via an N/C push-button Prevents the device with which it is used tripping if there is no supply voltage, while retaining the possibility of tripping via the control circuit for 60 hours minimum Not suitable for the supply circuits of moving machinery (e.g.: machine tools)	
1	4 062 87	Stand-alone release, 230 V~ supplied with battery	1.5
1	4 062 85	Replacement battery for release Cat. No. 4 062 87	

Pack	Cat.Nos	Motorised controls
		For mounting on the left-hand side of 1 module/pole MCBs, RCBOs and RCDs Enable the products with which they are used to be opened and closed remotely Take one control auxiliary and one signalling auxiliary The signalling auxiliary must be placed between the remote control and the control auxiliary
		<b>Standard</b>
		Control voltage   No. of modules
1	4 062 91	230 V~   1
		<b>With integrated automatic resetting</b> Automatically resets the product with which it is used, thus ensuring continuity of service
1	4 062 93	24-48 V~/=   2
1	4 062 95	230 V~   2
		<b>Accessories</b>
		<b>Padlocking</b>
2	4 063 03	Support for one Ø5 or Ø6 mm padlock for DX <sup>3</sup> MCBs and RCDs or isolating switches
1	0 227 97	Ø6 shackle type padlock
3	4 063 13	Ø5 shackle type padlock
		<b>Sealable screw cover - 4 separable poles</b>
2	4 063 04	For DX <sup>3</sup> MCBs, 1 module per pole
2	4 063 12	For DX <sup>3</sup> MCBs, 1.5 module per pole
		<b>Insulating shields</b> For DX <sup>3</sup> MCBs, 1 module per pole
1	4 063 05	Pole insulating shield (set of 6)
		<b>Spacing units with feedthrough</b> 0.5 module
10	4 063 07	
		<b>Aluminium terminals</b>
1	4 063 10	50 mm <sup>2</sup>
1	4 063 11	95 mm <sup>2</sup> for 1.5 module/pole MCBs
		<b>Terminal shields</b> For 1.5 module/pole products (set of 2)
1	4 063 06	

