

SEMICONDUCTOR FAN HEATER


CR 027 | up to 650W



- > Compact heater
- > Integrated thermostat
- > Clip fixing

- > Optical indicator
- > Temperature safety cut-out

Semiconductor fan heater prevents formation of condensation and frost and provides an evenly distributed interior air temperature in enclosures with electric/electronic components. The integrated thermostat is used to set the desired temperature.













TECHNICAL DATA

PTC resistor - temperature limiting			
to protect against overheating in case of fan failure,			
automatic reset			
airflow see table			
service life 50,000h at +25°C (+77°F)			
2-pole clamp 2.5mm², clamping torque 0.8Nm max			
plastic according to UL94 V-O, light grey			
thermostat control lamp			
clip for 35mm DIN rail, EN 60715			
vertical airflow (air outlet up) – other fitting positions possible			
100 x 128 x 165mm			
-45 to +70°C (-49 to +158°F)			
max. 90% RH (non-condensing)			
IP20 / II (double insulated)			
t t			





Art. No.	Operating voltage	Heating capacity ¹ (50 Hz)	Heatig capacity ¹ (60 Hz)	Inrush current max.	Pre-fuse T (time-delay)	Airflow, free flow	Setting range thermostat ²	Weight (approx.)
02700.0-00	220-240VAC, 50/60Hz	475W	550W	11A	6.3A	35m ³ /h	0 to +60°C	0.9kg
02701.0-00	220-240VAC, 50/60Hz	550W	650W	13A	A8	45m³/h	0 to +60°C	1.1kg
02700.9-00	100-120VAC, 50/60Hz	400W	550W	14A	8A	35m ³ /h	+32 to +140°F	0.9kg
02701.9-00	100-120VAC, 50/60Hz	510W	650W	15A	8A	45m ³ /h	+32 to +140°F	1.1kg

¹ at +20°C (+68°F) ambient temperature; ² Switch temperature difference 7K (±4K tolerance)