

## **MLFB-Ordering data**

#### 6SL3210-1KE15-8UF2



Figure similar

Client order no. :
Order no. :
Offer no. :
Remarks :

Item no. : Consignment no. : Project :

Rated d	ata
Input	
Number of phases	3 AC
Line voltage	380 480 V +10 % -20 %
Line frequency	47 63 Hz
Rated current (LO)	7.40 A
Rated current (HO)	6.00 A
Output	
Number of phases	3 AC
Rated voltage	400 V
Rated power IEC 400V (LO)	2.20 kW
Rated power NEC 480V (LO)	3.00 hp
Rated power IEC 400V (HO)	1.50 kW
Rated power NEC 480V (HO)	2.00 hp
Rated current (IN)	5.80 A
Rated current (LO)	5.60 A
Rated current (HO)	4.10 A
Max. output current	8.20 A
Pulse frequency	4.000 kHz
Output frequency for vector control	0 240 Hz
Output frequency for V/f control	0 550 Hz

Overload ca	apability
-------------	-----------

# Low Overload (LO)

 $150\ \%$  base load current IL for 3 s, followed by  $110\ \%$  base load current IL for 57 s in a  $300\ s$  cycle time

#### High Overload (HO)

 $200\,\%$  base load current IH for 3 s, followed by 150 % base load current IH for 57 s in a 300 s cycle time

General tech. specifications		
Power factor λ	0.70 0.85	
Offset factor cos φ	0.95	
Efficiency η	0.97	
Sound pressure level (1m)	49 dB	
Power loss	0.07 kW	
Filter class (integrated)	Unfiltered	

Ambient conditions		
Cooling	Air cooling using an integrated fan	
Cooling air requirement	0.005 m <sup>3</sup> /s (0.177 ft <sup>3</sup> /s)	
Installation altitude	1000 m (3280.84 ft)	
Ambient temperature		
Operation	-10 40 °C (14 104 °F)	
Transport	-40 70 °C (-40 158 °F)	
Storage	-40 70 °C (-40 158 °F)	
Relative humidity		

Max. operation	95 % At 40 °C (104 °F), condensation and icing not permissible

Closed-loop control techniques		
V/f linear / square-law / parameterizable	Yes	
V/f with flux current control (FCC)	Yes	
V/f ECO linear / square-law	Yes	
Sensorless vector control	Yes	
Vector control, with sensor	No	
Encoderless torque control	No	
Torque control, with encoder	No	



# **MLFB-Ordering data**

#### 6SL3210-1KE15-8UF2



03	E3210 TRE13 0012		Figure s	
Mechanical data		Com	Communication	
Degree of protection	IP20 / UL open type	Communication	PROFINET / EtherNet/IP	
Size	FSAA	Co	nnections	
Net weight	1.40 kg (3.09 lb)	Signal cable		
Width	73 mm (2.87 in)	Conductor cross-section	0.15 1.50 mm² (AWG 24 AWG 1	
Height	173 mm (6.81 in)	Line side		
Depth	178 mm (7.01 in)	Version	Plug-in screw terminals	
Inputs / out	tputs	Conductor cross-section	1.00 2.50 mm² (AWG 18 AWG 1	
tandard digital inputs		Motor end		
Number	6	Version	Plug-in screw terminals	
Switching level: 0→1	11 V	Conductor cross-section	1.00 2.50 mm² (AWG 18 AWG 1	
Switching level: 1→0	5 V	DC link (for braking resistor	)	
Max. inrush current	15 mA	Version	Plug-in screw terminals	
ail-safe digital inputs		Conductor cross-section	1.00 2.50 mm² (AWG 18 AWG 1	
Number	1	Line length, max.	15 m (49.21 ft)	
igital outputs		PE connection	On housing with M4 screw	
Number as relay changeover contact	1	Max. motor cable length		
Output (resistive load)	DC 30 V, 0.5 A	Shielded	50 m (164.04 ft)	
Number as transistor	1	Unshielded	100 m (328.08 ft)	
Output (resistive load)	DC 30 V, 0.5 A	S	tandards	
nalog / digital inputs		Compliance with standards	UL, cUL, CE, C-Tick (RCM)	
Number	1 (Differential input)			
Resolution	10 bit	CE marking	EMC Directive 2004/108/EC, Low-Vol Directive 2006/95/EC	
witching threshold as digital in	put			
0→1	4 V			
1→0	1.6 V			
nalog outputs				

# PTC/ KTY interface

Number

1 motor temperature sensor input, sensors that can be connected: PTC, KTY and Thermo-Click, accuracy  $\pm 5~^\circ\text{C}$ 

1 (Non-isolated output)



## **MLFB-Ordering data**


6SL3210-1KE15-8UF2



Figure similar

## Converter losses to EN 50598-2\*

Efficiency class	IE2
Comparison with the reference converter (90% / 100%)	-69.92 %



The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard EN 50598) of the relative torque generating current (I) over the relative motor stator frequency(f). The values are valid for the basic version of the converter without options/components.

\*converted values