

AXIS T8342 Door/Window Sensor

Wireless door/window sensor

AXIS T8342 Door/Window Sensor enables the triggering of events such as notification messages, illumination, and much more, when the door or window is opened. By communicating wirelessly with AXIS M5065 PTZ Network Camera or connected Z-Wave Plus[®] controllers, the door/window sensor can be used in small security solutions with less cabling. The wireless I/O connectivity also enables flexible installation as the sensor can easily be mounted on a door, window, or cabinet according to your needs.

- > **Wireless I/O connectivity**
- > **Z-Wave Plus[®] compatibility**
- > **S2 security compliant**
- > **Battery included**



AXIS T8342 Door/Window Sensor

Supported products	AXIS M5065 PTZ Network Camera Compatible with other Z-Wave Plus® control devices	Approvals	EMC FCC Part 15 Subpart C, ICES-003 Class B, VCCI Class B, EN 301 489-1 V2.1.1, EN 301 489-13 V2.1.1 Radio EN 300 220-2 v3.1.1, EN 300 220-2 V3.1.1
Network		Dimensions	Sensor: 31 x 15 x 70 mm (1.22 x 0.59 x 2.76 in) Magnet: 11 x 15 x 70 mm (0.43 x 0.59 x 2.76 in)
Supported protocols	Z-Wave Plus®. For more information on the supported command classes, see the product's User Manual	Weight	38 g (0.08 lbs)
General		Included accessories	Installation guide, mounting kit, 2 x CR2450 3.0 V Lithium battery
Casing	Plastic Color: white	Warranty	Axis 3-year warranty, see www.axis.com/warranty
Sustainability	PVC-free		
Power	2 x CR2450 3.0 V Lithium battery Battery life: 1 year ^a		
Distance	Transmitting range up to 100 meters (328 ft)		
Frequency	908.42 MHz (US), 922.5 MHz (JP), 868.42 MHz (EU)		
Operating conditions	-10 °C to 40 °C (14 °F to 104 °F)		
Storage conditions	-20 °C to 60 °C (-4 °F to 140 °F)		

a. Measured at 10 triggers per day.

Environmental responsibility:
www.axis.com/environmental-responsibility