

VGA & Audio to HDMI Converter

HCV0101



The HCV0101 converts VGA input into HDMI to allow PC users to show their image not only on the PC's monitor, but could also on TV, to have a large display. The conversion is along with the R/L audio. It offers solutions for digital entertainment center, HDTV retail and show site, HDTV, DVD and Projector factory, noise space and security concerns, data center control, information distribution, conference room presentation, school and corporate training environments.

Features:

- Easy to Use: Install in seconds, no need of setting
- Conversion: It could convert PC's VGA video and R/L audio into complete HDMI
- Extra VGA and R/L audio outputs: the outputs could be connected back to PC's monitor and speakers
- Automatic positioning of the image
- HDCP pass-through

Package Content:

- VGA & Audio to HDMI Converter
- Power supply
- User Manual

Output Video	HDMI 1.2a
Resolutions VGA	640x480 60 Hz 75 Hz
	800x600 60 Hz 75 Hz
	1024x768 60 Hz 75 Hz
	1280x720 60 Hz 75 Hz
	1280x768 60 Hz 75 Hz
	1280x960 60 Hz 75 Hz
	1280x1024 60 Hz 75 Hz
Resolutions HDTV	480i / 576i / 480p / 576p / 720p / 1080i / 1080P
Frequency	Up to 165 MHz
Video Amplifier Bandwidth	1.65 Gbps / 165 MHz
Size(W-H-D)	89mmW x 29mmH x 68mmD
Weight(Net)	0.68kgs
Operating Temperature	0 °C to +70°C
Operating Humidity	10% to 85 % RH (no condensation)
Storage Temperature	-10°C to +80°C
Storage Humidity	5% to 95 % RH (no condensation)
External Power Supply	5V DC@1A
Regulatory Approvals	CE,FCC