

RADIATRON


- BS rated and approved to DIN, VDE, SEMKO, UL
- Touchproof & panel sealed
- For 1/4" x 1/4" and 5 x 20mm fuses
- Touchproof fuseholders with Dual Capability also Push Fit Mounting



Panel Mounting Fuseholders


Miniature fuseholder FEP 031.1001

For 5 x 20 mm fuses
10A/500V \approx SEV, 6.3A/250V \approx VDE and 7A BS
Mounting hole 13 mm \varnothing
Bayonet cap fuse carrier
Solder tags 2.8 x 0.5 mm
Test voltage 4 KV, 50Hz, 1 minute




Fuseholder (UL approved) FER 031.2001

For 1 1/4" x 1/4" fuses
Waterproof from front
10A/500V \approx SEV,
6.3A/250V \approx VDE
15A/250V \approx UL
Mounting hole 13 mm \varnothing
Bayonet cap fuse carrier
Solder tag connections
Test voltage 4 KV, 50Hz, 1 minute




Touchproof fuseholder To DIN 41664 FEB 031.1401

For 5 x 20 mm fuses
10A/500V \approx SEV, 6.3A/250V \approx VDE and SEMKO
Mounting hole 13 mm \varnothing
Solder tags 2.8 x 0.5 mm
VDE/SEMKO/SEV approval
Test voltage 4 KV, 50Hz, 1 minute



Touchproof fuseholder with "push-in" mounting FEF031.1091


For 5 x 20 mm fuses
6.3A/250V
Mounting hole: \varnothing 13 mm
Test voltage 4 KV/50 Hz, 1 min



Voltage Selectors


Voltage selector with built-in fuseholder SWP 033.1000/SWR 033.2000

For 5 x 20 mm fuses
SWP 033.1000
For 1 1/4" x 1/4" fuses
SWR 033.2000
Bayonet cap fuse carrier
6 voltages set by using
Screwdriver or coin after
removing the cap
Standard voltage marking
110/125/150/200/220/250V
Rating - 6.3A/250V \approx VDE




Touchproof fuseholder (Flush mounting) FEI 031.1431

For 5 x 20 mm fuses
10A/500V \approx SEV, 6.3A/250V \approx VDE and SEMKO
Mounting hole 13 mm \varnothing
Bayonet cap fuse carrier
Solder tags 2.8 x 0.5 mm
VDE/SEMKO/SEV approval
Test voltage 4 KV, 50Hz, 1 minute



Touchproof fuseholder For both 20mm x 5mm and 1/4" x 1/4" fuses


FEU031.1673 flat black socket
FEK031.1661 carrier for 1/4" x 1/4" fuses
FEK031.1663 carrier for 20 mm x 5 mm fuses
6.3A/250V to VDE, semco
12A/250V to UL, CSA
Mounting hole: \varnothing 13 mm
Bayonet cap fuse carriers
Test voltage 4KV, 50Hz, 1 minute.



Printed Circuit Fuseholders


Fuseholder for printed circuit mounting (Vertical) FAP 031.3601

For 5 x 20 mm fuses
Vertical mounting
10/250 \approx SEV,
6.3A/250V \approx VDE
Bayonet cap fuse carrier
SEV, VDE approved
Test voltage 3 KV, 50Hz, 1 minute




Spring clip fuseholders for printed circuits OG 751.0035

For fuses 5x20mm and 1 1/4" x 1/4"
10A/250V \approx
OG 751.0045
For fuses 5 x 20 mm




Fuseholder for printed circuit mounting (Horizontal) FAS 031.3511

For 5 x 20 mm fuses
Angled mounting 9° from
horizontal
10/250 \approx SEV,
6.3A/250V \approx VDE
Bayonet cap fuse carrier
SEV approved
Test voltage 3 KV, 50Hz, 1 minute




Open mounted fuseholder for printed circuits OG 031.8001/8002

10A/250V \approx SEV,
6.3A/250V \approx VDE
For 5 x 20 mm fuses
OG 031.8001
For fuses 1 1/4" x 1/4"
OG 031.8002
Test voltage 3 KV,
50Hz, 1 minute



Anti-rotational washer

For locking fuse holders with mounting
hole of 13 mm \varnothing
without punching a complicated D-lock



Order No.	Size					
	A	B	C	D	E	F
031.8001	29	9.5	4	16	25	+0.4 0
031.8002	41	14	4	18.5	37.5	+0.6 0

Manufactured in Switzerland