

FU8310

Secvest 2WAY Wireless Fire Alarm Button

The secvest 2WAY wireless fire alarm button is a detector of the Secvest (or the Terxon with a wireless expansion module). By pressing the button, you can easily and quickly trigger a fire alarm. In the Secvest, the wireless fire button assigns a zone with the "fire" characteristic. This zone is monitored and the button will trigger an alarm even when the alarm panel is disarmed. In the system settings of the Secvest, you can define whether a call should be made to an emergency call center in addition to the acoustic and visual alarm. With corresponding batteries (3 V lithium) the wireless fire button has a service life of approx. 24 months. The range is approx. 50 meters.



Product highlights:

- Convenient flush–mounting
 - Reliably triggers the fire alarm
 -
 -
 -
-

FU8310

Secvest 2WAY Wireless Fire Alarm Button

Technical Data

power supply	3V lithium battery, size CR2450	Degree of safety	2
Battery service life	up to 2 years	Housing material	thermoplastics
Environmental class	II (-10°C to +50°C)	Operating frequency	868.6625 Mhz FM, narrow band
Coverage	up to 50 m (depending on environment)	Dimensions (HxWxD)	85x85x52 mm